

**EVALUATED METERING EQUIPMENT LIST**  
**LAST REVIEWED: 1/17/2023**

NO.	MANUFACTURER	MODEL NO.	DESCRIPTION/USE	RESULT	DATE EVALUATED	EQUIPMENT PHOTO
1	B-Line	78205141112	Multi Meter Socket, 2 Sockets, 1 phase. No lid sealing mechanism - Unacceptable. Jaws have no inner tension clip - Unacceptable.	Unacceptable	6/12/2002	
2	Eaton Cutler-Hammer	1MP3124R 1MP1122R - 1MP5206R	Multi Meter Socket/Breaker, 2-5 Sockets, 125 or 200 Amp, 120/240 VAC, Ring Type	Acceptable	7/25/2002	Photo
3	Eaton Cutler-Hammer	3MM312R 1MM212R - 1MM520R 3MM212R - 3MM520R	Modular Meter Socket/Breaker, 2-5 Sockets, 125 or 200 Amp, 120/240 VAC or 120/208Y VAC, 3MM has 5th Neutral Jaw	Acceptable	10/15/2001	Photo
4	Eaton Cutler-Hammer	35MM140R1240	Modular Meter Socket/Breaker, 320 Amp, Ringless, Lever Bypass, 1 Phase, 120/240 VAC	Acceptable	9/25/2019	
5	Eaton Cutler-Hammer	37MM140R12 37MM140R12 - 37MM440R12	Modular Meter Socket/Breaker, 1-4 Sockets, 320 Amp, Lever Bypass, 3 Phase, 208/120 VAC Wye, 240/120 VAC Delta	Acceptable	12/6/2013	Photo
6	Eaton Cutler-Hammer	37MM420R12 37MM120R12 - 37MM420R12	Modular Meter Socket/Breaker, 1-4 Sockets, 200 Amps, Lever Bypass, 3 Phase, 208/120 VAC Wye, 240/120 VAC Delta	Acceptable	6/7/2014	Photo
7	Eaton Cutler-Hammer	37SS220R	Modular Meter/Breaker, 2 Sockets, 200 Amp, 3 Phase, 208/120 VAC Wye; 240/120 VAC Delta. Line and load conductors are in the same compartment - Unacceptable.	Unacceptable	12/17/2004	Photo
8	Eaton Cutler-Hammer	CHM6G6G5GSU	Meter Socket/Breaker/Receptables, 120/240 VAC, 1 Phase, 3 Wire. Does not have the correct tamper proof lid or neutral connection.	Unacceptable	4/26/2006	Photo
9	Eaton Cutler-Hammer	CHM7N7N5GS	1 PHASE, 120/240 VAC, 125 amp, Neutral must be accessible in the meter socket and needs tamper proof lid with 2 points securing it 180 degrees apart	Unacceptable	8/28/2014	Photo
10	Eaton Cutler-Hammer	MHM200P	Mobile Home Pedestal, Meter Socket/Breaker, 200 Amp, 1 Phase, 120/240 VAC. Socket is rated for 170 amps continuous - Unacceptable.	Unacceptable	8/21/2003	Photo
11	Eaton	U2,3,4,5R1121BCRCH	Modular Gang Meter Sockets, 120/208, 1 phase, 3 Wire, No service disconnect (breaker) 2,3,4,5 sockets	Unacceptable	4/24/2020	
12	Eaton	U2,42352TCRCH	Modular Gang Meter Sockets, 120/208, 1 phase, 3 Wire, No service disconnect (breaker) 2 and 4 socket	Unacceptable	4/24/2020	
13	Eaton	URT2R2332UCH	Modular Gang Meter Sockets, 120/240, 1 phase, 3 Wire, No service disconnect (breaker) 2 socket, no tamper proof lid	Unacceptable	4/24/2020	
14	G.E.	TMP 12212R, 12312R, 12412R, 12512R	Modular Meter Socket/Breaker, 2-5 Sockets, 125 Amp, 1 Phase, 3 Wire, 120/240 VAC, Ring Type. A blank lid will only be used to cover an empty socket position with no meter socket installed and only on the bottom socket position. The lid will be secured with a sealing hasp and locking device.	Acceptable	7/11/2008	Photo
15	G.E.	TMP 8412R & TMP 8512R	Modular Meter Socket/Breaker, 4-5 Sockets, 125 Amp, 1 Phase, 3 Wire, 120/240 VAC, Ring Type. A blank lid will only be used to cover an empty socket position with no meter socket installed and only on the bottom socket position. The lid will be secured with a sealing hasp and locking device.	Acceptable	12/6/2008	
16	G.E.	TMP38120RT TMP38120RT - TMP312320RT	Modular Meter Socket/Breaker, 1-3 Sockets, 200 Amp, 3 Phase, 208/120 VAC Wye; 240/120 VAC Delta. Test Block Bypass - Unacceptable.	Unacceptable	5/15/2014	Photo
17	G.E.	TMP 8220R, 8320R, 8420R	Modular Meter Socket/Breaker, 2-4 Sockets, 200 Amp, 1 Phase, 120/240 VAC. *The 2 socket unit requires a secure load bus passageway to be acceptable.	*Acceptable	4/3/2003	Photo
18	G.E.	TMPR 12512R, 12212R	Modular Meter Socket/Breaker, 2 and 5 Sockets, 125 Amp, 1 Phase, 208Y/120 VAC. Ringless - Unacceptable.	Unacceptable	7/2/2008	Photo
19	G.E.	TMPR312122R TMPR312122R - TMPR312422R	Modular Meter Socket Breaker, 1-4 Sockets, 225 Amp, 3 Phase, Lever Bypass, 208/120 VAC Wye; 240/120 VAC Delta	Acceptable	5/20/2014	Photo
20	G.E.	TSM420CSCU	Meter/Breaker, 200 Amp, 1ph, 120/240 VAC. No tamper proof lid and no neutral connection in socket - Unacceptable.	Unacceptable	9/7/2005	Photo
21	Midwest Electric	M038C033	Meter Socket/Breaker/Receptables, 125 Amp. No neutral connection - Unacceptable.	Unacceptable	3/28/2002	Photo
22	Midwest Electric	M281C1	Meter Socket/Breaker, 200 Amp	Acceptable	3/28/2002	Photo
23	Midwest Electric	M281C1B6H	Pedestal, Meter Socket/Breaker, 2 Sockets, 200 Amp, Underground Feed	Acceptable	3/21/2001	Photo
24	Midwest Electric	M281C1P6H	Pedestal, Meter/Breaker, 200 amp, Underground Feed	Acceptable	3/20/2001	Photo
25	Midwest Electric	M281CB1	Meter Socket/Breaker, 200 Amp	Acceptable	3/28/2002	Photo
26	Milbank	CP3B11115P	Meter Socket/Breaker, 200 Amp, 1 Phase, 3 Wire, 120/240 VAC, Ring Type, UG lockable compartment. Mounted on concrete pad. Unacceptable - Test Bypass Block	Unacceptable	11/19/2009	
27	Milbank	CP3B5181FS50WCSSP1	Pedestal, Meter Socket/Breaker, 100 Amp/200 Amp, 3 Phase, 480 VAC. Ringless - Unacceptable. Customer would need line side disconnect.	Unacceptable	9/2/2011	
28	Milbank	CP3B54139R42SGWFSP1 or CP3B54139R42DSWFSP1	ATM Pedestal, Meter Socket, 320 Amp, 1 Phase, 120/240 VAC. Ringless, Lever Bypass, Customer Load compartment, Sealable/Lockable using CNP locks on Utility Connection Compartment	Acceptable	10/16/2016	
29	Milbank	MC24TB	Meter Socket/Breaker, 1 Phase, 120/240 VAC, 3 wire. Line and load conductors are in the same compartment - Unacceptable.	Unacceptable	2/24/2012	Photo

30	Milbank	MPAP-(amp)-MB	Meter Socket/Breaker, 200 Amp. Safety concerns.	Unacceptable	3/27/2001	Photo
31	Milbank	U1252-X	Meter Socket, 2 Sockets, 200 Amp. Ringless - Unacceptable. No neutral connection in socket - Unacceptable.	Unacceptable	7/24/2012	Photo
32	Milbank	U3241-0-200	Meter Socket/Breaker, 200 Amp, 240 volt, 1 phase, 3 wire	Acceptable	7/11/2002	Photo
33	Milbank	U5240 Versa-Ped	Meter Service Pedestal with stabilizer foot for direct burial, underground feed, circuit below socket . Meter Socket/Breaker, 200 amp. 1 Phase.	Acceptable	1/10/2008	Photo
34	Milbank	U5300-0-75	Meter Socket/Breaker,125 amp, 1 Phase, no tamper proof lid, no neutral and Line and Load in same compartment	Unacceptable		
35	Milbank	U5882	Multi Meter Socket/Breaker, 2 Sockets. 160 Amps - Unacceptable, Ringless - Unacceptable, No neutral connection - Unacceptable.	Unacceptable	7/24/2012	Photo
36	Milbank	46317	320 Amp Pedestal, Ringless, Lin & Load in same compartment	Unacceptable		
37	Milbank	U5927-O-200	Meter Service Pedestal with stabilizer foot for direct burial, underground feed, Meter Socket/Breaker, 200 amp, 1 Phase, 120/240 VAC	Acceptable	4/24/2018	Photo
38	Murray	DL143W7	Modular Meter Socket/Breaker, 1 Socket, 320 Amp, Lever Bypass, 3 Phase, 4 Wire, 600 VAC, 400 Amp Breaker. Same as SIEMENS W3MM1200	Acceptable	10/27/2005	Photo
39	Murray	MP4312	Multi Meter Socket/Breaker, 3 Sockets, 200 Amp, 1 Phase, 120/240 VAC. Same as Siemens SP4312.	Acceptable	3/30/2005	Photo
40	Siemens	60950301	Multi Meter Socket/Breaker, 3 Sockets, 200 Amp, 1 Phase, 3 Wire, 120/240 Volt, Ring Type, Tamper Proof. No neutral contact in meter socket - Unacceptable.	Unacceptable	11/17/2004	Photo
41	Siemens	MC0816MB1200T	Meter Socket/Breaker, 200 Amp. Line and load conductors in same compartment - Unacceptable.	Unacceptable	4/22/2002	Photo
42	Siemens	SP4312	Multi Meter Socket/Breaker, 3 Sockets, 200 Amp, 1 Phase, 120/240 VAC. Same as Murray MP4312.	Acceptable	3/30/2005	Photo
43	Siemens	W3MM1200 W3MM1200-W3MM4200	Modular Meter Socket/Breaker, 1-4 Sockets, 200 Amp, Lever Bypass, 3 Phase, 208/120 VAC Wye; 240/120 VAC Delta	Acceptable	1/12/2005	Photo
44	Siemens	W3MM1400	Modular Meter Socket/Breaker, 1 Socket, 320 Amp, Lever Bypass, 3 Phase, 4 Wire, 600 VAC, 400 Amp Breaker	Acceptable	10/27/2005	Photo
45	Siemens	WC2040B2T2J	Modular Meter Socket/Breaker, 200 Amp, 1 Phase, 120/280Y, 240 VAC Max	Acceptable	9/20/2013	Photo
46	Siemens	WCL2040B1T2RJ	Modular Meter Socket/Breaker, 200 Amp, Lever Bypass, 1 Phase, 240 VAC Max. 200 Amp Lever Bypass sockets not allowed for 1 phase.	Unacceptable	8/20/2013	Photo
47	Siemens	WCT2040B1T2RJ	Modular Meter Socket/Breaker with Test Block Bypass, 200 Amp, 1 Phase, 120/208Y, 240 VAC Max. Test Block Bypass Assembly - Unacceptable.	Unacceptable	8/20/2013	Photo
48	Siemens	WML13100RJ	Modular Meter Socket/Breaker, 1 Socket, 225 Amp, 200 Amp continuous, Lever Bypass Ringless 3 Phase, 120/240 VAC 4W DELTA, 120/208 VAC 4W WYE. Labeling must be in the metering compartment stating voltage and current rating of the meter socket.	Acceptable	5/7/2018	Photo
49	Siemens	WML11400RJ	Modular Meter Socket/Breaker, 400 Amp, Lever Bypass, 1 Phase, 120/240 VAC. Labeling must be in the metering compartment stating voltage and current rating of the meter socket.	Acceptable	4/7/2010	Photo
50	Siemens	WML13225RJ WML13225RJ - WML43225RJ	Modular Meter Socket/Breaker, 1-4 Sockets, 225 Amp, Lever Bypass, 3 Phase, 208/120 VAC Wye, 240/120 VAC Delta	Acceptable	6/7/2014	Photo
51	Siemens	WMM2U (Old Model) WMM21125(J) - WMM51225(J) & WMM52125(J)	Modular Meter Socket/Breaker, 2-5 sockets, 125 or 225 Amp, 120/240 VAC or 120/208Y VAC	Acceptable	9/8/2006	Photo
52	Siemens	WP2211	Multi Meter Socket/Breaker, 2 Sockets, 200 Amp, 1 Phase, 120/240 VAC	Acceptable	10/29/2021	Photo
53	Siemens	WP4312	Multi Meter Socket/Breaker, 3 Sockets, 200 Amp, 1 Phase, 120/240 VAC or 120/208Y VAC	Acceptable	2/23/2012	Photo
54	Siemens	MM0202B1200, MM0202B1150	Meter Socket/Breaker, 1 Socket, 200 Amp, 1 Phase, 120/240 VAC , tamper proof lid, 4 jaw, 200 Amp or 150 Amp breaker	Acceptable	4/24/2020	Photo
55	Square D	EZM113125 EZM113125 - EZM115125	Modular Meter Socket/Breaker, 3-5 Sockets, 125 Amp, 1 Phase, 120/240 VAC. Square D universal 225 amp socket. *Neutral wire kit must be installed in each socket.	*Acceptable	3/28/2014	Photo
56	Square D	EZM112225 EZM112225 - EZM115225	Modular Meter Socket/Breaker, 2-5 Sockets, 225 Amp, 1 Phase, 120/240 VAC. *Neutral wire kit must be installed in each socket.	*Acceptable	4/11/2014	Photo
57	Square D	EZM313125 EZM313125 - EZM315125	Modular Meter Socket/Breaker, 3-5 Sockets, 125 Amp, 1 Phase, 120/208Y VAC. Square D 225 amp universal socket.	Acceptable	4/25/2014	Photo
58	Square D	EZM312225 EZM312225 - EZM315225	Modular Meter Socket/Breaker, 2-5 Sockets, 200 Amp, 208Y/120 VAC, 300 VAC max.	Acceptable	9/17/2004	Photo
59	Square D	EZML332225 EZML331225 - EZML334225	Modular Meter Socket/Breaker, 1-4 Sockets, 225 Amp, Lever Bypass, 3 Phase, 4 Wire, 208/120 VAC Wye; 240/120 VAC Delta	Acceptable	5/23/2014	Photo
60	Square D	EZML111400 EZML111400 - EZML112400	Modular Meter Socket/Breaker, 1-2 Sockets, 320 Amp, Lever Bypass, 1 Phase, 120/240 VAC. Socket has 5th Jaw for 120/240 VAC service - Unacceptable.	Unacceptable	5/11/2006	Photo
61	Square D	MP22125 - MP55125	Multi Meter Socket/Breaker, 2-5 Sockets, 125 Amp, 1 Phase, 120/240 VAC. Square D universal 225 amp socket. *Neutral wire kit must be installed in each socket.	*Acceptable	4/25/2014	Photo

62	Square D	MP86200	Multi Meter Socket/Breaker, 6 Sockets, 125 Amp, 1 Phase, 120/240 VAC. Square D universal 200 amp socket, no Bypass, Ring Type.	*Acceptable	9/13/2017	
63	Square D	MP42200 MP44125 - MP85200	Multi Meter Socket/Breaker, 2 and 5 Socket, 125/200 Amp, 1 Phase, 120/240 VAC. Unsecured meter socket compartment - Unacceptable.	Unacceptable	4/25/2014	Photo
64	Square D	MP44125 MP44125 - MP64200	Multi Meter Socket/Breaker, 3, 4 and 6 Sockets, 125/200 Amp, 1 Phase, 120/240 VAC. Contractors must install neutral kits before CenterPoint Energy installs the meters - No unsecured meter socket compartments allowed. Acceptable.	Acceptable	4/25/2014	Photo
65	Square D	SC 1624M125C, RC 1624M125C	Meter Socket, 125 Amp, 1 Phase, 120/240 VAC. Line and load conductors are not separated - Unacceptable. "RC" version does not use ring for securing meter to can - Unacceptable. Service connection compartment lid does not have secure sealing mechanism - Unacceptable.	Unacceptable	1/13/2004	
66	Square D	SC816F200F	Meter Socket/Breaker, 200 Amp, 1 Phase, 120/240 VAC. No tamper proof lid - Unacceptable. No neutral connection in socket - Unacceptable.	Unacceptable	1/15/2013	Photo

### EVALUATED EQUIPMENT FOR SPECIFIC APPLICATIONS

NO.	MANUFACTURER	MODEL NO.	DESCRIPTION/USE	RESULT	DATE EVALUATED	EQUIPMENT PHOTO
1	Bison Pre-Fab	3267	Pedestal, Meter Socket/Load Center supplied by Cotswold 2000 Construction for use in downtown beautification projects. Measures 50"x40"x18". 3 Phase, 4 Wire Y. Approved if meter socket is ring type and tamper proof. Service conductors must be in conduit. Main switch cover will be locked.	Acceptable	12/2/2002	Photo
2	Emerson (Marconi)	PEIL-BBCRF11RHA1	Pedestal for Power Transfer Switch. Meter socket is a Milbank 200 Amp, 240 volt, UL listed, ring type with service conductors installed in conduit separate from load conductors.	Acceptable	7/5/2005	Photo
3	Emerson Network Power Series	PESBBBRRY11HHA1W	Pedestal for Power Transfer Switch. Approved with the following conditions: Meter socket will be UL listed with a ring type, tamper proof lid. The center of the meter socket opening shall be at least 3 feet above ground level. The service entrance conductors must be installed in rigid conduit from the concrete pad to the meter socket.	Acceptable	11/11/2016	
4	Emerson Network Power Series	2PE26MCBFFRF1ZMWZ1	Pedestal for Power Transfer Switch. Three power inputs - 100 amp utility, 100 amp generator and a 30 amp generator. Approved with the following conditions: Meter socket will be UL listed with a ring type, tamper proof lid. The center of the meter socket opening shall be at least 3 feet above ground level. The service entrance conductors must be installed in rigid conduit from the concrete pad to the meter socket.	Acceptable	1/25/2007	Photo
5	Generac	RXUW200A3, RXUW150A3, RBU200A3 AND RBU150A3 Must be equipped with Tamper Proof Kit G0074100	Generac Combination Meter Socket and Transfer System Enclosures - 120/240V, Single Phase, 3 Wire, 200 and 150 Amp	Acceptable	11/10/2022	Photo
6	Milbank	CP3B11115A22	Pedestal for Traffic Signals, Meter/Breaker, 200 Amp, 120/240 VAC or 120/280Y VAC. To be mounted on concrete pad. Unacceptable - Test Bypass Block	Unacceptable	4/6/2005	Photo
7	Milbank	CP3B11119A42SP9	Meter Socket/Breaker Pedestal, 1 ph, 600 VAC Socket, 200 Amp Cont, Ring Type Tamper Proof Lid, 100 Amp Main Breaker, 3 Lockable Compartments, UL Listed -Unacceptable because of the Test Bypass Block	Unacceptable	11/14/2014	Photo
8	Milbank	CP3B4280PS22WCSSP1	Pedestal for Car Charging Station, Meter Socket/Breaker, 200 Amp, 3 ph, 277/480 VAC	Acceptable	12/21/2010	
9	Milbank	CP3B5281DK32ADGSP1	Meter Socket/Breaker Pedestal, 3 ph, 4 wire, 277/480 VAC Socket, 200 Amp -Unacceptable because of the Test Bypass Block	Unacceptable		
10	Milbank	CP3B51219KSP1	Meter Socket/Breaker Pedestal, 1 ph, 3 wire, 100 AMP Socket, - Unacceptable because of the Test Bypass Block	Unacceptable		
11	Milbank	CP3B41119K22AOSP1	Pedestal with customer load center for 'Way Finding', 1 Phase, 3 Wire, 120/240 VAC, 100 Amp breaker, Stainless Steel, Window in Lid, Ring Socket and tamper proof - Openway meter will sync with lid closed, Line and Load wire separated and lockable.	Acceptable	4/2/2018	
12	Milbank	CP3B41219K22AOSP1	Pedestal with customer load center for 'Way Finding', 1 Phase, 3 Wire, 120/208 VAC, 100 Amp breaker, Stainless Steel, Window in Lid, Ring Socket and tamper proof - Openway meter will sync with lid closed, Line and Load wire separated and lockable.	Acceptable	4/2/2018	Photo
13	Myers Custom Products	MEUG16A-M100-MOD	Pedestal for Traffic Control for City of Houston. Meter Socket/Breaker, 100 amp	Acceptable	3/15/2001	Photo
14	Myers Custom Products	MEUG16A-M200-MOD	Pedestal for Traffic Control for City of Houston. Meter Socket/Breaker, 200 Amp	Acceptable	3/22/2001	Photo
15	Marconi	PEIL-BBCRF11RHA1	Pedestal for Power Transfer Switch for SBC applications. An acceptable 200 amp Milbank meter socket is mounted on unit.	Acceptable	7/5/2005	Photo
16	Mica Corp.	Freeway Lighting	Pedestal for TXDOT freeway lighting. 100 Amp, 480 VAC	Acceptable	5/23/2005	
17	TESCO Controls	Job #T-35725, Cat. # 26-000	Pedestal, Meter Socket/Breaker, 125 Amp, 1 phase, 240 volt, 600 VAC. 100 amp main breaker. Ring type socket lid. UL listed, Type 3R outdoor enclosure. Meter compartment has a flap with a clear plexiglass window that can be opened. Meter compartment is lockable to prevent access to wiring. Line wire service compartment separate and lockable.	Acceptable	4/1/2009	Photo

18	Strong Box	MPS-C20-22K	Stainless Steel Pedestal, Meter Socket/Breaker, 1 phase, 240 volt, 600 VAC. 200 amp main breaker. Ring type socket, Tamper Proof lid. UL listed, Type 3R Enclosure	Acceptable	9/1/2015	Photo
----	------------	-------------	--	------------	----------	-------

19	W.E. Manufacturing	Type D, Custom made per job	Meter Pedestal with Customer Load Center, 120/240 VAC, 1 Phase, 125 Amps, Ring Type, Tamper Proof Meter Socket	Acceptable	8/17/2016	Photo
----	--------------------	-----------------------------	--	------------	-----------	-------